



|   |  |  |   |  |  |   |
|---|--|--|---|--|--|---|
| <p style="text-align: center;"><b>USER MANUAL</b></p>  <p style="text-align: center;"><b>TRUE WIRELESS T302A</b></p> | <p>Fully charge the earphone before using.<br/>Tip: Keep the earphone away from your credit card or other magnetic storage media; otherwise, the stored information may be lost due to demagnetization.</p> <p>How to connect with the Bluetooth earphone (Note: Use iPhone for example)<br/>For customer's convenience of operation, the left- and right-channel stereo of the two Bluetooth earphones has been paired and connected before leaving factory.</p> <ul style="list-style-type: none"> <li>●Dual-earphone mode – Initial use of the earphone</li> </ul> <ol style="list-style-type: none"> <li>1. For the first use, after charging with the charging box, the white LED of the charging box is on; place the left (L) and right (R) headphones in the charging box for activation.</li> <li>2. Remove the left (L) and right (R) headphones from the charging box. The left (L) and right (R) headphones implement TWS pairing automatically, and have a prompt tone when completing the TWS pairing.</li> <li>3. Start the Bluetooth on your phone, and search for Bluetooth headset.After the Bluetooth headset is found, click Pair to complete connection.</li> </ol> | <ul style="list-style-type: none"> <li>●Single-earphone mode (Using any of the earphones independently)</li> </ul> <ol style="list-style-type: none"> <li>1.when the headset is removed from the charging base, the headset is automatically turned on and the red and blue lights are alternately flashing and paired.</li> <li>2. Start the Bluetooth on your phone, and search for Bluetooth headset.</li> <li>3.After the Bluetooth headset is found, click Pair to complete connection.</li> </ol> <p><b>Basic Operations</b><br/><b>Auto power-on/off:</b> When the headset is taken out of the charging box, the headset is automatically powered on and the TWS connection is successfully established, accompanied by a voice prompt. The headset will be automatically powered off if pairing is not completed in 3 minutes. When the headset is put into the charging box, the headset is automatically powered off and enters the charging state, accompanied by a voice prompt.</p> <p><b>Manual TWS pairing:</b> When the left and right earphones enter the pairing state, double-tap an earphone to start TWS pairing, and the indicator blinks in red and blue alternatively. After the successful pairing, a voice prompt can be heard on both the left and right earphones.</p> | <p><b>Connection:</b> Assume that the left and right earphones have completed pairing. When you take either earphone out of the charging box, the indicator blinks in red and blue alternatively, and the mobile phone searches for T302A. Tap Connect, and a voice prompt can be heard. If the pairing record has been cleared, the headset must enter the TWS pairing mode again; otherwise, only one earphone can be used.</p> <p><b>Receiving a call:</b> When there is an incoming call, you can double-click the left earphone (L) or right earphone (R) to receive the call, and meanwhile a "Beep" prompt tone can be heard.</p> <p><b>Terminating a call:</b> During a call, you can double-click the left earphone (L) or right earphone (R) to terminate the call, and meanwhile a "Beep" prompt tone can be heard.</p> <p><b>Canceling a call:</b> After you dial a call, you can double-click the left earphone (L) or right earphone (R) to cancel the call, and meanwhile a "Beep" prompt tone can be heard.</p> <p><b>Playing or pausing music:</b> When the music is being played, you can double-tap the left earphone (L) or</p> | <p>right earphone (R) to pause the music, or repeat the same operation to play the music again.</p> <p><b>Automatic re-connection:</b> After the earphone are powered on, they are actively re-connected to the last paired one devices.</p> <p><b>iOS battery level display:</b> After the earphone is connected to the iOS, the battery level of the earphone can be displayed.</p> <p><b>Low-voltage alarm:</b> A voice prompt is played every 5 minutes until the headset is powered off.</p> <p><b>Anti-lost alarm:</b> When the headset is far away from you or is abnormally disconnected, a voice prompt can be heard. An attempt will be made to reconnect the headset in 3 minutes. Three minutes later, the headset will be automatically powered off.</p> <p><b>Charger and Battery</b><br/>Before using any charger to charge this earphone, check whether the specifications of the charger meet requirements. The recommended output voltage of the charger is DCSV+/-0.25V, and the recommended output current is 100 mA to 500 mA. An over-high charging voltage may damage the earphone.</p> | <p><b>Warning:</b> Use the recommended charger whenever possible. Use of other types of chargers may violate the warranty terms of the equipment and results in danger. If the charging cable is delivered with the earphone, connect the cable to a CCC-certified charger or computer to charge the earphone.</p> <p><b>Charging the Battery</b><br/>The earphone use embedded charging battery that cannot be removed. Do not attempt to remove the battery from the earphone or the charging box; otherwise, the earphone may be damaged. If the earphone is not used in a long time, keep it in a cool and well-ventilated place, and charge the earphone once every two months.</p> <ol style="list-style-type: none"> <li>1.When the LED indicator connected earphone flash red with a voice “please charge”, put the earphone into the charging box. Otherwise the earphone will power off automatically.</li> <li>2.If both the earphone and charging box are out of power, insert the cable of the charger into the Micro-USB port on the charging box, and plug the charger into the AC socket. The charging box and earphone will be charged simultaneously.</li> </ol> | <ol style="list-style-type: none"> <li>3. The earphone is charged through two metal contacts during charging in the box, and the indicator blinks blue while charging. The full charge takes about two hours. The indicator goes off when the earphone is fully charged. Then you can take out your earphone for use. When the charging box is being charged, the four indicators blink blue in sequence. The full charge takes about two hours. The four indicators become steady blue when the charging box is fully charged. Then you can disconnect the charger from the socket and charging box.</li> <li>4.A fully charged battery of earphone can provide about 3.5 hours of talk time, or 70 hours of standby time. The actual talk time and standby time may vary with cell phones, settings, use methods, and environment.</li> </ol> |
|   | 1  | 2  | 3   | 4  | 5  | 6   |

|  |   |  |   |  |  |  |
|--|---|--|---|--|--|--|
| <p style="text-align: center;"><b>HƯỚNG DẪN SỬ DỤNG</b></p>  <p style="text-align: center;"><b>TAI NGHE BLUETOOTH TWS T302A</b></p> | <p>Sạc đầy tai nghe trước khi sử dụng.<br/>Mẹo: Giữ tai nghe cách xa thẻ tín dụng hoặc phương tiện lưu trữ từ tính khác; tránh trường hợp thông tin được lưu trữ có thể bị mất do quá trình khử từ.</p> <p>Cách kết nối với tai nghe Bluetooth (Lưu ý: Ví dụ sau áp dụng khi dùng iPhone)<br/>Để thuận tiện cho khách hàng, bên trái và phải của hai tai nghe Bluetooth đã được ghép nối và kết nối với nhau trước khi xuất xưởng.</p> <ul style="list-style-type: none"> <li>● Chế độ tai nghe kép - Lần đầu sử dụng tai nghe</li> </ul> <ol style="list-style-type: none"> <li>1. Đối với lần sử dụng đầu tiên, sau khi sạc với hộp sạc, đèn LED của hộp sạc hiển thị màu trắng; đặt tai nghe bên trái (L) và phải (R) vào hộp sạc để kích hoạt.</li> <li>2. Tháo tai nghe bên trái (L) và phải (R) khỏi hộp sạc. Tai nghe bên trái (L) và phải (R) sẽ ghép nối tự động và có âm báo nhanh khi hoàn thành ghép nối TWS.</li> <li>3. Khởi động Bluetooth trên điện thoại và tìm kiếm tai nghe Bluetooth. Sau khi tìm thấy tai nghe Bluetooth, nhấp vào Ghép nối để hoàn tất kết nối.</li> </ol> <ul style="list-style-type: none"> <li>● Chế độ một tai nghe (Sử dụng độc lập cho 1 trong 2 bên tai nghe)</li> </ul> | <ol style="list-style-type: none"> <li>1. Khi tai nghe được tháo khỏi hộp sạc, tai nghe sẽ tự động được bật, đèn Led hiển thị màu Đỏ-Xanh nhấp nháy sẵn sàng trong trạng thái ghép nối.</li> <li>2. Khởi động Bluetooth trên điện thoại và tìm kiếm tai nghe Bluetooth.</li> <li>3.Sau khi tìm thấy tai nghe Bluetooth, bấm Ghép nối để hoàn tất kết nối.</li> </ol> <p><b>Hoạt động cơ bản</b><br/>Tự động bật/ tắt nguồn: Khi tai nghe được lấy ra khỏi hộp sạc, tai nghe sẽ tự động được bật và kết nối TWS được thiết lập thành công, kèm theo lời nhắc bằng giọng nói. Tai nghe sẽ tự động tắt nếu việc ghép nối không hoàn thành sau 3 phút. Khi tai nghe được đưa vào hộp sạc, tai nghe sẽ tự động tắt và đi vào trạng thái sạc, kèm theo lời nhắc bằng giọng nói.</p> <p><b>Ghép nối thủ công TWS:</b> Khi tai nghe bên trái và bên phải trong trạng thái ghép nối, chạm liên tiếp hai lần vào tai nghe để bắt đầu ghép nối TWS kèm theo đèn Led nhấp nháy Xanh-Đỏ. Sau khi kết nối thành công, có thể nghe thấy lời nhắc bằng giọng nói trên cả tai nghe bên trái và bên phải.</p> <p><b>Kết nối:</b> Đảm bảo 2 tai nghe đã được kết nối với nhau. Khi lấy 1 trong 2 tai nghe ra, tìm kiếm thiết bị</p> | <p>trên điện thoại, chọn T302A và nhấn kết nối. Khi kết nối thành công, sẽ nghe âm báo bằng giọng nói. Trong trường hợp 2 tai nghe đã bị xóa kết nối, chỉ có 1 tai nghe được sử dụng.<br/><b>Nhận cuộc gọi:</b> Khi có cuộc gọi đến, chạm liên tiếp hai lần vào tai nghe bên trái (L) hoặc tai nghe phải (R) để nhận cuộc gọi kèm theo âm báo "Beep".</p> <p><b>Kết thúc cuộc gọi:</b> Trong khi gọi, chạm liên tiếp hai lần vào tai nghe bên trái (L) hoặc tai nghe phải (R) để kết thúc cuộc gọi kèm theo âm báo "Beep".</p> <p><b>Hủy cuộc gọi:</b> Sau khi quay số cuộc gọi, chạm hai lần liên tiếp vào tai nghe bên trái (L) hoặc tai nghe phải (R) để hủy cuộc gọi kèm theo âm báo nhắc "Beep".</p> <p><b>Phát hoặc tạm dừng nhạc:</b> Khi nhạc đang được phát, chạm hai lần liên tiếp vào tai nghe bên trái (L) hoặc tai nghe phải (R) để tạm dừng nhạc hoặc lặp lại thao tác tương tự để phát lại nhạc.</p> <p><b>Kết nối lại tự động:</b> Sau khi tai nghe được bật, chúng được kết nối lại với các thiết bị được ghép nối cuối cùng.</p> <p><b>Hiển thị mức pin của iOS:</b> Sau khi tai nghe được kết nối với iOS, có thể xem được mức pin của tai nghe.</p> | <p><b>Cảnh báo pin yếu:</b> Một lời nhắc thoại được phát cứ sau 5 phút cho đến khi tắt tai nghe.</p> <p><b>Báo động chống mất:</b> Khi 1 tai nghe ở xa hoặc bị ngắt kết nối bất thường, có thể nghe thấy lời nhắc bằng giọng nói. Tai nghe sẽ cố gắng kết nối lại trong 3 phút. Ba phút sau đó, tai nghe sẽ tự động tắt.</p> <p><b>Bộ sạc và pin</b><br/>Trước khi sử dụng bất kỳ bộ sạc nào để sạc tai nghe, hãy kiểm tra xem các thông số kỹ thuật của bộ sạc có đáp ứng yêu cầu hay không. Điện áp đầu ra được đề nghị của bộ sạc là DCSV +/- 0,25V và dòng điện đầu ra được đề nghị là 100 mA đến 500 mA. Điện áp sạc quá cao có thể làm hỏng tai nghe.</p> <p><b>Cảnh báo:</b> Khuyến cáo nên dùng bộ sạc theo đúng tiêu chuẩn được đề nghị. Việc sử dụng các loại bộ sạc khác có thể dẫn đến nguy hiểm.</p> <p><b>Sạc pin</b><br/>Tai nghe sử dụng pin sạc không thể tháo rời. Không tìm cách tháo pin ra khỏi tai nghe hoặc hộp sạc; nếu không, tai nghe có thể bị hỏng. Nếu tai nghe không được sử dụng trong một thời gian dài, hãy giữ nó ở nơi mát mẻ và thông thoáng, và sạc tai nghe hai tháng một lần.</p> | <ol style="list-style-type: none"> <li>1.Khi đèn LED hiển thị đỏ kèm theo âm báo bằng giọng nói"please charge", vui lòng sạc tai nghe. Nếu không, tai nghe sẽ tự động tắt nguồn.</li> <li>2.Nếu cả tai nghe và hộp sạc đều hết pin, đặt tai nghe vào hộp sạc, cắm sạc hộp sạc qua cổng USB-Type C. Hộp sạc và tai nghe sẽ được sạc đồng thời.</li> <li>3. Tai nghe được sạc qua hai điểm tiếp xúc kim loại trong hộp sạc và đèn báo nhấp nháy màu xanh trong khi sạc. Sạc đầy mất khoảng hai giờ. Đèn báo sẽ tắt khi tai nghe được sạc đầy. Sau đó, có thể lấy tai nghe ra để sử dụng. Đèn LED hiển thị màu trắng nhấp nháy khi hộp sạc đang được sạc. Sạc đầy mất khoảng hai giờ. Đèn LED hiển thị màu trắng sẽ hết nhấp nháy khi hộp sạc được sạc đầy.</li> <li>4. Tai nghe khi sạc đầy có thể cung cấp khoảng 3,5 giờ đàm thoại hoặc 70 giờ trong thời gian chờ. Thời gian nói chuyện thực tế và thời gian chờ có thể khác nhau tùy theo điện thoại di động, cài đặt, phương thức sử dụng và môi trường.</li> </ol> |  |
|  | 7   | 8  | 9   | 10   | 11   |  |

105双铜 单色双面印刷 风琴折60x90mm