## Canon



# **SELPHY** SQUARE QX10 COMPACT PHOTO PRINTER

## Hướng dẫn bắt đầu

## TIẾNG VIỆT

- Trước khi sử dụng máy in, đảm bảo đọc kỹ hướng dẫn này, bao gồm cả phần "Cảnh báo an toàn" (2).
- Đọc hướng dẫn này sẽ giúp bạn sử dụng máy in đúng cách.
- Giữ kỹ hướng dẫn để có thể sử dụng sau này.

## ┙ Cảnh báo an toàn

- Đảm bảo đọc kỹ hướng dẫn sử dụng này để thao tác sản phẩm một cách an toàn.
- Thực hiện theo hướng dẫn để tránh chấn thương cho người thao tác sản phẩm hoặc người khác.

## A CẢNH BÁO

Cảnh báo có nguy cơ gây chấn thương nghiêm trong hoặc tử vong.

- Chỉ sử dụng nguồn điện được chỉ định trong hướng dẫn này cho sản phẩm.
- Không tháo rời hoặc sửa đổi sản phẩm.
- Không để sản phẩm chịu tác động hoặc rung lắc mạnh.
- Không chạm vào bất kỳ phần bên trong lộ ra nào của máy ảnh.
- Ngừng sử dụng sản phẩm nếu có các hiện tượng bất thường như phát ra khói hoặc có mùi la.
- Không sử dụng các dung môi hữu cơ như cồn, xăng hoặc chất pha loãng sơn để vệ sinh sản phẩm.
- Không để cho sản phẩm bị ẩm. Không cắm vật thể lạ hoặc cho chất lỏng vào sản phẩm.
- Không sử dụng sản phẩm ở nơi có xăng dầu dễ cháy.

Làm vây có thể gây ra điện giật hoặc cháy nổ.

 Không chạm vào sản phẩm khi kết nối với ổ điện trong cơn bão sấm sét.

Làm vậy có thể gây giật điện.

- Định kỳ dùng vải khô lau sạch bụi bám trên chân cắm và ổ điện.
- Không dùng tay ướt cắm hoặc rút chân cắm.
- Không sử dụng sản phẩm nếu chân cắm không được cắm hoàn toàn vào ổ điện.
- Không để chân cắm và đầu cực vào bụi bẩn hoặc tiếp xúc với đinh ghim hoặc vật kim loại khác.
- Không đặt vật nặng trên dây nguồn. Không làm hỏng, bẻ gãy hoặc sửa đổi dây nguồn.
- Không dùng vải hoặc các vật khác bọc sản phẩm do sản phẩm vẫn còn nóng khi đang sử dụng hoặc ngay sau khi sử dụng.
- Không để sản phẩm kết nối với nguồn điện trong khoảng thời gian dài.
- Không sạc sản phẩm tại nhiệt độ ngoài phạm vi 5 40 °C (41 104 °F). Làm vậy có thể gây ra điện giật hoặc cháy nổ.



 Thực hiện theo các chỉ dẫn để tắt sản phẩm ở các nơi không được phép sử dụng.

Nếu không, hiệu ứng sóng điện từ của sản phẩm có thể làm cho thiết bị khác bi truc trặc và thâm chí gây ra tại nan.

**A** THẬN TRỌNG

Cảnh báo có nguy cơ gây chấn thương.

Không chạm vào các bộ phận bên trong của sản phẩm.
 Làm vậy có thể gây chấn thương.

## Trước khi sử dung


- Ảnh in bằng sản phẩm này chỉ được dùng vào mục đích giải trí cá nhân.
   Nghiêm cấm in trái phép các tài liệu có bản quyền.
- Bảo hành máy in chỉ có giá trị tại quốc gia hoặc khu vực mua hàng. Trong trường hợp máy in gặp trục trặc khi ở nước ngoài, vui lòng gửi về khu vực mua hàng trước khi liên hệ với Bộ phận hỗ trợ khách hàng.


## 🚄 Thành phần của bộ sản phẩm

- □ SELPHY SQUARE QX10
- □ Cáp sạc

□ Hôp mực mẫu

- □ Giấy dán mẫu
- Bao gồm cả hướng dẫn sử dụng bản giấy.
- Mua riêng lẻ Mưc in màu / Bô nhãn (XS-20L).
- Cáp sạc phụ kiện là cáp chỉ sử dụng để sạc và không thể sử dụng cho việc giao tiếp.





- (1) Đèn CHARGE (Sạc)
- (2) Đèn STATUS (Trạng thái)
- (3) Nút nguồn
- (4) Cổng sạc
- (5) Công tắc tắt bắt buộc
- (6) Cần gạt đẩy

- (7) Nhãn mã QR
- (8) Nắp ngăn chứa hộp mực

Giấy mực

- (9) Khe xuất giấy
- (10) Nắp ngăn giấy
- (11) Nút mở



- Đặt máy in trên bàn hoặc bề mặt phẳng và ổn định khác. Không được đặt máy in trên bề mặt không ổn định hoặc nghiêng.
- Không được đặt đồ vật có thể gây vướng giấy trong khi in trước khay xuất giấy.
- Bạn cần nhãn mã QR khi đăng ký lại máy in, chẳng hạn khi bạn thay đổi smartphone. Hãy chụp mã QR với chức năng máy ảnh của smartphone của ban và bảo quản cần thân.



Nếu giấy mực bị lỏng, xoay nhẹ bánh răng để kéo căng giấy. Không chạm vào giấy mực.









#### Đèn báo

Đèn STATUS (Trạng thái)	Đèn CHARGE (Sạc)	Trạng thái
Tát	Tắt	Nguồn tắt (Không sạc)
	Nhấp nháy màu xanh lá cây chậm	Đang sạc (Tắt nguồn)
	Phát sáng màu xanh lá cây	Đã sạc đầy (Tắt nguồn)*1
Nhấp nháy màu trắng chậm	Tắt	Đang khởi động máy in
Nhấp nháy màu trắng	Tắt	Đang xử lý
Nhấp nháy màu trắng nhanh	Tắt	Gỡ giấy đã in.
Phát sáng màu trắng	Tắt	Sẵn sàng in (Không sạc)*2
	Nhấp nháy màu xanh lá cây	Sẵn sàng in (Mức pin yếu)
	Nhấp nháy màu xanh lá cây chậm	Sẵn sàng in (Đang sạc)
	Phát sáng màu xanh lá cây	Sẵn sàng in (Đã sạc đầy)
Nhấp nháy màu đỏ chậm	Nhấp nháy màu xanh lá cây chậm	Ngoài phạm vi nhiệt độ vận hành nên quá trình sạc đã tạm dừng.
Nhấp nháy màu đỏ	Tắt	Đã xảy ra lỗi. Kiểm tra thông báo ứng dụng.
	Nhấp nháy màu xanh lá cây	Mức pin yếu, bạn không thể in. Sạc pin.
Nhấp nháy màu đỏ nhanh	Tắt	Đã xảy ra lỗi. Tắt nguồn và bật lại.
	Nhấp nháy màu xanh lá cây nhanh	Đã xảy ra lỗi pin.

- \*1 Sau một lúc, đèn CHARGE (Sạc) sẽ tắt.
- \*2 Bạn có thể kiểm tra mức pin bằng cách nhấn nút Nguồn trong trạng thái Sẫn sàng in (Không sạc).
  - Đèn CHARGE (Sạc) nhấp nháy 2 lần:
     Mức pin yếu những vẫn tiếp tục sử dụng được máy in.
  - Đèn CHARGE (Sạc) nhấp nháy 3 lần: Mức pin đủ dùng.








## Chuẩn bị

#### Sạc pin



- Kết nối máy in và bộ điều hợp AC sạc USB (bán riêng) với cáp sạc phụ kiện.
  - Đèn CHARGE (Sạc) bắt đầu nhấp nháy màu xanh lá cây và bắt đầu sạc. Khi đèn CHARGE (Sạc) phát sáng màu xanh lá cây, pin đã sạc đầy.

## 🏲 Cài đặt ứng dụng

Cần sử dụng ứng dụng smartphone SELPHY Photo Layout cùng với sản phẩm này để in.


- 1 Tải xuống và cài đặt phiên bản mới nhất của SELPHY Photo Layout.
  - Tim "SELPHY Photo Layout" trong App Store (khi dùng iPhone, iPad) hoặc Google Play (khi dùng smartphone Android) và cài đặt SELPHY Photo Layout.
- 2 Khởi động SELPHY Photo Layout.
- Bật dịch vụ định vị trên smartphone.
- Tắt chế độ tiết kiệm pin và các chức năng khác làm giảm việc tiêu hao pin của smartphone.
- Thực hiện theo hướng dẫn trên màn hình.



 Để tìm hiểu thông tin về cách thao tác máy in, chẳng hạn như cách nạp giấy hoặc thay đổi hộp mực, tham khảo [Printer Manual] của SELPHY Photo Layout.







- Đặt giấy với bề mặt in (bề mặt không có logo Canon) úp xuống dưới, cẩn thân không cham vào bề mặt in.
- Không sử dụng giấy đã in hoặc giấy có chữ viết hoặc các ký hiệu khác.
- Giấy sẽ chạy ra từ khe xuất giấy nhiều lần trong khi in. Không kéo giấy ra cho đến khi thông báo cho việc gỡ giấy hiển thị trên smartphone.
- Không làm gián đoạn giao tiếp cho đến khi in xong. Nếu giao tiếp bị gián đoạn, việc in có thể chỉ được thực hiện giữa chừng.
- Không mở nắp ngăn chứa hộp mực hoặc nắp ngăn giấy trong khi máy in đang hoạt động.
- Nếu trạng thái Sẵn sàng in tiếp tục trong khoảng 10 phút, nguồn sẽ tự động tắt. Để tiếp tục in, nhấn nút Nguồn.








7

EC815\_GS\_VI.indd 7



Kích thước Khoảng 102,2 × 143,3 × 31,0 mm

(4,02 × 5,65 × 1,23 in.) (Không bao gồm phần nhô ra)

Trọng lượng Khoảng 445 g (15,70 oz.) (chỉ thân máy in)

Nhiệt đô vân hành 5 °C - 40 °C (41 - 104 °F)

Đô ẩm vân hành 20 - 80%

Ngõ vào định mức DC 5,0 V ±0,5 V, tối đa 900 mA

Công nghệ in In nhiệt thăng hoa mực (có lớp phủ)

Độ phân giải  $287 \times 287$  dpi Thang màu 256 mức / màu

Dung lượng khay giấy 10 tờ

Cỡ giấy Khoảng 72,0 × 85,0 mm (2,84 × 3,35 in.)

Phạm vi in Có thể lựa chọn bằng ứng dụng ở

khoảng 68 x 68 mm (2,7 x 2,7 in.), khoảng 65 x 65 mm (2,6 x 2,6 in.), hoặc khoảng 62 x 62 mm (2,4 x 2,4 in.)

Số tờ có thể in Khoảng 20 tờ (nhiệt độ phòng, pin sạc đầy)

Tốc độ in (1 tờ) Khoảng 43 giây (nhiệt độ phòng)

- Bộ điều hợp và thời gian sạc Sử dụng bộ sạc với nguồn điện định mức DC 5,0 V, 1000 mA hoặc hơn để sạc sản phẩm. Việc sạc sẽ mất khoảng 2 tiếng ở nhiệt độ phòng, nhưng thời gian này sẽ tăng lên tùy theo điều kiện của pin được sử dụng và môi trường sac.
- Tất cả dữ liệu đều dựa trên các thử nghiệm của Canon.
- Thông số kỹ thuật hoặc kiểu dáng của máy in có thể thay đổi mà không thông báo trước.

## Ĺ Những điều cần chú ý về Wi-Fi (Mạng LAN không dây)

- Sản phẩm này được gắn với một thiết bị không dây. Số model là CD1158 (bao gồm model WM321 của mô-đun WLAN).
- Các quốc gia và khu vực cho phép sử dụng WLAN

Một số quốc gia và khu vực hạn chế sử dụng WLAN và việc sử dụng bất hợp pháp có thể bị phạt theo quy định của quốc gia hoặc địa phương. Để tránh vi phạm luật về WLAN, truy cập trang web của Canon để xem các khu vực được phép sử dụng. Lưu ý rằng Canon không chịu trách nhiệm cho bất kỳ vấn đề nào phát sinh do sử dụng WLAN tại các quốc gia và khu vực khác.

- Những hành vi sau có thể bị phạt:
  - Thay đổi hoặc điều chỉnh sản phẩm Tháo nhãn chứng nhân khỏi sản phẩm
- Không sử dụng chức năng mạng LAN không dây của thiết bị này gần thiết bị v tế hoặc thiết bị điện tử khác.
  - Sử dụng chức năng mạng LAN không dây gần thiết bị y tế hoặc thiết bị điện tử khác sẽ làm ảnh hưởng đến hoạt động của các thiết bị đó.









Sản phẩm này có thể bị nhiễu do sóng vô tuyến phát ra từ các thiết bị khác. Để tránh bị ảnh hưởng, khi sử dụng sản phẩm, đảm bảo tránh xa các thiết bị trên, hoặc tránh sử dụng thiết bị cùng lúc với sản phẩm này.

Do đó, Canon Inc. tuyên bố rằng thiết bị này phù hợp với Chỉ thị 2014/53/  $\,$  EU.

Toàn bộ văn bản tuyên bố về sự phù hợp EU có sẵn tại địa chỉ mạng sau đâv:

http://www.canon-europe.com/ce-documentation

Thông số kỹ thuật mạng LAN không dây Băng tần: 2401 MHz - 2473 MHz Công suất tần số vô tuyến tối đa: 11.4 dBm

#### CANON EUROPA N.V.

Bovenkerkerweg 59, 1185 XB Amstelveen, The Netherlands **CANON INC.** 

30-2, Shimomaruko 3-chome, Ohta-ku, Tokyo 146-8501, Japan

Complies with IMDA Standards DB00671









1/17/2020 5:00:17 PM

## Những điều cần chú ý về bảo mật

Do Wi-Fi sử dụng sóng vô tuyến để truyền tín hiệu, nên khi sử dụng cáp mạng LAN phải đặc biệt chú ý đến vấn đề bảo mật. Khi sử dụng Wi-Fi, cần chú ý những điều sau.

- Đường truyền bị giám sát
   Bên thứ ba với mục đích xấu có thể giám sát đường truyền Wi-Fi với ý
   đồ thu thập dữ liệu ban đạng gửi.
- Truy cập mạng trái phép
   Các bên thứ ba với mục đích xấu có thể sử dụng bất hợp pháp sản phẩm này nếu họ có thể truy cập thông tin có trong mã QR.
   Bạn nên sử dụng ứng dụng smartphone SELPHY Photo Layout để thay đổi mật khẩu mạng khi cần thiết.

#### Những điều cần chú ý trước khi sửa chữa, vứt bỏ hoặc chuyển quyền sở hữu

Trước khi chuyển quyền sở hữu, vứt bỏ sản phẩm hoặc đưa sản phẩm đi sửa chữa, thực hiện những bước sau đây để khôi phục lại cài đặt ban đầu.

Bật nguồn. → Nhấn và giữ nút Nguồn. Sau 1 giây, đèn STATUS (Trạng thái) sẽ tắt. → Tiếp tục nhấn nút Nguồn. → Khi đèn STATUS (Trạng thái) bắt đầu nhấp nháy, nhả nút Nguồn.

## Bạn nên sử dụng các phụ kiện chính hãng của Canon

Sản phẩm này được thiết kế để đạt hiệu quả tối ưu khi sử dụng với các phụ kiện chính hãng của Canon.

Canon sẽ không chịu trách nhiệm cho bất kỳ hư hỏng nào đối với sản phẩm và/hoặc tai nạn, chẳng hạn như cháy, v.v. do trục trặc của các phụ kiện không chính hãng Canon (ví dụ như rò rỉ và/hoặc nổ pin). Lưu ý rằng bảo hành không áp dụng đối với sửa chữa các trục trặc do phụ kiện không chính hãng Canon, tuy nhiên bạn có thể yêu cầu sửa chữa và chấp nhận thanh toán chi phí.





THẬN TRỌNG VỚT BỔ PIN ĐÃ SỬ DỤNG THEO QUY ĐỊNH CỦA ĐỊA PHƯƠNG.

Dòng điện một chiều

Sẵn sàng


12







1/17/2020 5:00:17 PM



- App Store, iPhone và iPad là thương hiệu của Apple Inc., đã đăng ký tại Hoa Kỳ và các quốc gia khác.
- Google Play và Android là thương hiệu của Google LLC.
- QR Code là thương hiệu của Denso Wave Inc.
- Wi-Fi®, Wi-Fi Alliance®, WPA™ và WPA2™ là thương hiệu thuộc quyền hoặc thương hiệu đã đăng ký của Wi-Fi Alliance.
- Tất cả các thương hiệu khác là tài sản của chủ sở hữu tương ứng.



0. 5:00:17 PM



- Nghiêm cấm in lại, truyền bá hoặc lưu trữ bất kỳ phần nào của hướng dẫn này trong hệ thống truy lục mà không được sự cho phép của Canon.
- Canon bảo lưu quyền thay đổi nội dung của hướng dẫn này vào bất kỳ thời điểm nào mà không cần thông báo trước.
- Hình minh họa trong hướng dẫn này có thể khác đôi chút so với thiết bị thực tế.
- Bất kể mục nào ở trên, Canon sẽ không chịu trách nhiệm đối với những hư hỏng do thao tác sản phẩm sai.
- Để tìm hiểu thông tin về phần mềm bên thứ ba, tham khảo phần "Phần mềm bên thứ ba" ở cuối hướng dẫn này.










1/17/2020 5:00:17 PM



Sản phẩm này bao gồm phần mềm bên thứ ba.

#### XySSL

Portions based on XySSL Copyright (C) 2006-2008 Christophe Devine Copyright (C) 2009 Paul Bakker <polarssl\_maintainer at polarssl dot org> All rights reserved.

#### MBEDTLS

Portions based on MBEDTLS
Copyright (C) 2006-2015, ARM Limited, All Rights Reserved
SPDX-License-Identifier: Apache-2.0
Distributed on an "AS IS" BASIS, WITHOUT
WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied.
You may obtain a copy of the Apache License at
http://www.apache.org/licenses/LICENSE-2.0

Apache License Version 2.0, January 2004 http://www.apache.org/licenses/

#### TERMS AND CONDITIONS FOR USE. REPRODUCTION, AND DISTRIBUTION

#### Definitions.

"License" shall mean the terms and conditions for use, reproduction, and distribution as defined by Sections 1 through 9 of this document.

"Licensor" shall mean the copyright owner or entity authorized by the copyright owner that is granting the License.

"Legal Entity" shall mean the union of the acting entity and all other entities that control, are controlled by, or are under common control with that entity. For the purposes of this definition, "control" means (i) the power, direct or indirect, to cause the direction or management of such entity, whether by contract or otherwise, or (ii) ownership of fifty percent (50%) or more of the outstanding shares, or (iii) beneficial ownership of such entity.

"You" (or "Your") shall mean an individual or Legal Entity exercising permissions granted by this License.

"Source" form shall mean the preferred form for making modifications, including but not limited to software source code, documentation source, and configuration files.

"Object" form shall mean any form resulting from mechanical transformation or translation of a Source form, including but not limited to compiled object code, generated documentation, and conversions to other media types.

"Work" shall mean the work of authorship, whether in Source or Object form, made available under the License, as indicated by a copyright notice that is included in or attached to the work (an example is provided in the Appendix below).







"Derivative Works" shall mean any work, whether in Source or Object form, that is based on (or derived from) the Work and for which the editorial revisions, annotations, elaborations, or other modifications represent, as a whole, an original work of authorship. For the purposes of this License, Derivative Works shall not include works that remain separable from, or merely link (or bind by name) to the interfaces of the Work and Derivative Works thereof.

"Contribution" shall mean any work of authorship, including the original version of the Work and any modifications or additions to that Work or Derivative Works thereof, that is intentionally submitted to Licensor for inclusion in the Work by the copyright owner or by an individual or Legal Entity authorized to submit on behalf of the copyright owner. For the purposes of this definition, "submitted" means any form of electronic, verbal, or written communication sent to the Licensor or its representatives, including but not limited to communication on electronic mailing lists, source code control systems, and issue tracking systems that are managed by, or on behalf of, the Licensor for the purpose of discussing and improving the Work, but excluding communication that is conspicuously marked or otherwise designated in writing by the copyright owner as "Not a Contribution."


"Contributor" shall mean Licensor and any individual or Legal Entity on behalf of whom a Contribution has been received by Licensor and subsequently incorporated within the Work.

- 2. Grant of Copyright License. Subject to the terms and conditions of this License, each Contributor hereby grants to You a perpetual, worldwide, non-exclusive, no-charge, royalty-free, irrevocable copyright license to reproduce, prepare Derivative Works of, publicly display, publicly perform, sublicense, and distribute the Work and such Derivative Works in Source or Object form.
- 3. Grant of Patent License. Subject to the terms and conditions of this License, each Contributor hereby grants to You a perpetual, worldwide, non-exclusive, no-charge, royalty-free, irrevocable (except as stated in this section) patent license to make, have made, use, offer to sell, sell, import, and otherwise transfer the Work, where such license applies only to those patent claims licensable by such Contributor that are necessarily infringed by their Contribution(s) alone or by combination of their Contribution(s) with the Work to which such Contribution(s) was submitted. If You institute patent litigation against any entity (including a cross-claim or counterclaim in a lawsuit) alleging that the Work or a Contribution incorporated within the Work constitutes direct or contributory patent infringement, then any patent licenses granted to You under this License for that Work shall terminate as of the date such litigation is filed.
- 4. Redistribution. You may reproduce and distribute copies of the Work or Derivative Works thereof in any medium, with or without modifications, and in Source or Object form, provided that You meet the following conditions:
  - (a) You must give any other recipients of the Work or Derivative Works a copy of this License; and









- (c) You must retain, in the Source form of any Derivative Works that You distribute, all copyright, patent, trademark, and attribution notices from the Source form of the Work, excluding those notices that do not pertain to any part of the Derivative Works; and
- (d) If the Work includes a "NOTICE" text file as part of its distribution, then any Derivative Works that You distribute must include a readable copy of the attribution notices contained within such NOTICE file, excluding those notices that do not pertain to any part of the Derivative Works, in at least one of the following places: within a NOTICE text file distributed as part of the Derivative Works; within the Source form or documentation, if provided along with the Derivative Works, or, within a display generated by the Derivative Works, if and wherever such third-party notices normally appear. The contents of the NOTICE file are for informational purposes only and do not modify the License. You may add Your own attribution notices within Derivative Works that You distribute, alongside or as an addendum to the NOTICE text from the Work, provided that such additional attribution notices cannot be construed as modifying the License.

You may add Your own copyright statement to Your modifications and may provide additional or different license terms and conditions for use, reproduction, or distribution of Your modifications, or for any such Derivative Works as a whole, provided Your use, reproduction, and distribution of the Work otherwise complies with the conditions stated in this License.

- 5. Submission of Contributions. Unless You explicitly state otherwise, any Contribution intentionally submitted for inclusion in the Work by You to the Licensor shall be under the terms and conditions of this License, without any additional terms or conditions. Notwithstanding the above, nothing herein shall supersede or modify the terms of any separate license agreement you may have executed with Licensor regarding such Contributions.
- Trademarks. This License does not grant permission to use the trade names, trademarks, service marks, or product names of the Licensor, except as required for reasonable and customary use in describing the origin of the Work and reproducing the content of the NOTICE file.
- 7. Disclaimer of Warranty. Unless required by applicable law or agreed to in writing, Licensor provides the Work (and each Contributor provides its Contributions) on an "AS IS" BASIS, WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied, including, without limitation, any warranties or conditions of TITLE, NON-INFRINGEMENT, MERCHANTABILITY, or FITNESS FOR A PARTICULAR PURPOSE. You are solely responsible for determining the appropriateness of using or redistributing the Work and assume any risks associated with Your exercise of permissions under this License.



- 8. Limitation of Liability. In no event and under no legal theory, whether in tort (including negligence), contract, or otherwise, unless required by applicable law (such as deliberate and grossly negligent acts) or agreed to in writing, shall any Contributor be liable to You for damages, including any direct, indirect, special, incidental, or consequential damages of any character arising as a result of this License or out of the use or inability to use the Work (including but not limited to damages for loss of goodwill, work stoppage, computer failure or malfunction, or any and all other commercial damages or losses), even if such Contributor has been advised of the possibility of such damages.
- 9. Accepting Warranty or Additional Liability. While redistributing the Work or Derivative Works thereof, You may choose to offer, and charge a fee for, acceptance of support, warranty, indemnity, or other liability obligations and/or rights consistent with this License. However, in accepting such obligations, You may act only on Your own behalf and on Your sole responsibility, not on behalf of any other Contributor, and only if You agree to indemnify, defend, and hold each Contributor harmless for any liability incurred by, or claims asserted against, such Contributor by reason of your accepting any such warranty or additional liability.

#### END OF TERMS AND CONDITIONS

APPENDIX: How to apply the Apache License to your work.

To apply the Apache License to your work, attach the following boilerplate notice, with the fields enclosed by brackets "[]" replaced with your own identifying information. (Don't include the brackets!) The text should be enclosed in the appropriate comment syntax for the file format. We also recomment that a file or class name and description of purpose be included on the same "printed page" as the copyright notice for easier identification within third-party archives.

Copyright [yyyy] [name of copyright owner]

Licensed under the Apache License, Version 2.0 (the "License"); you may not use this file except in compliance with the License. You may obtain a copy of the License at

http://www.apache.org/licenses/LICENSE-2.0

Unless required by applicable law or agreed to in writing, software distributed under the License is distributed on an "AS IS" BASIS, WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied.

See the License for the specific language governing permissions and limitations under the License.

#### snprintf


You can get the Standard Version from https://www.ijs.si/software/snprintf/(snprintf\_2.2.tar.gz).

Copyright 1999, Mark Martinec. All rights reserved.









The Frontier Artistic License Version 1.0
Derived from the Artistic License at OpenSource.org.
Submitted to OpenSource.org for Open Source Initiative certification.

#### Preamble

The intent of this document is to state the conditions under which a Package may be copied, such that the Copyright Holder maintains some semblance of artistic control over the development of the package, while giving the users of the package the right to use and distribute the Package in a more-or-less customary fashion, plus the right to make reasonable modifications.

#### Definitions

"Package" refers to the script, suite, file, or collection of scripts, suites, and/or files distributed by the Copyright Holder, and to derivatives of that Package created through textual modification.

"Standard Version" refers to such a Package if it has not been modified, or has been modified in accordance with the wishes of the Copyright Holder.

"Copyright Holder" is whoever is named in the copyright statement or statements for the package.

"You" is you, if you're thinking about copying or distributing this Package.

"Reasonable copying fee" is whatever you can justify on the basis of media cost, duplication charges, time of people involved, and so on. (You will not be required to justify it to the Copyright Holder, but only to the computing community at large as a market that must bear the fee.)

"Freely Available" means that no fee is charged for the item itself, though there may be fees involved in handling the item. It also means that recipients of the item may redistribute it under the same conditions they received it.


#### Terms

- You may make and give away verbatim copies of the source form of the Standard Version of this Package without restriction, provided that you duplicate all of the original copyright notices and associated disclaimers.
- You may apply bug fixes, portability fixes, and other modifications derived from the Public Domain or from the Copyright Holder. A Package modified in such a way shall still be considered the Standard Version.









- a) Use the modified Package only within your corporation or organization, or retain the modified Package solely for personal use.
- b) Place your modifications in the Public Domain or otherwise make them Freely Available, such as by posting said modifications to Usenet or an equivalent medium, or placing the modifications on a major archive site such as ftp.uu.net, or by allowing the Copyright Holder to include your modifications in the Standard Version of the Package.
- c) Rename any non-standard executables so the names do not conflict with standard executables, which must also be provided, and provide a separate manual page (or equivalent) for each non-standard executable that clearly documents how it differs from the Standard Version.
- d) Make other distribution arrangements with the Copyright Holder.
- 4. You may distribute the programs of this Package in object code or executable form, provided that you do at least ONE of the following:
  - a) Distribute a Standard Version of the executables and library files, together with instructions (in the manual page or equivalent) on where to get the Standard Version.
  - b) Accompany the distribution with the machine-readable source of the Package with your modifications.
  - c) Accompany any non-standard executables with their corresponding Standard Version executables, give the non-standard executables non-standard names, and clearly document the differences in manual pages (or equivalent), together with instructions on where to get the Standard Version.
  - d) Make other distribution arrangements with the Copyright Holder.
- 5. You may charge a reasonable copying fee for any distribution of this Package. You may charge any fee you choose for support of this Package. You may not charge a fee for this Package itself. However, you may distribute this Package in aggregate with other (possibly commercial) programs as part of a larger (possibly commercial) software distribution provided that you do not advertise this Package as a product of your own.
- 6. The scripts and library files supplied as input to or produced as output from the programs of this Package do not automatically fall under the copyright of this Package, but belong to whomever generated them, and may be sold commercially, and may be aggregated with this Package.







- Scripts, suites, or programs supplied by you that depend on or otherwise make use of this Package shall not be considered part of this Package.
- The name of the Copyright Holder may not be used to endorse or promote products derived from this software without specific prior written permission.
- THIS PACKAGE IS PROVIDED "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTIBILITY AND FITNESS FOR A PARTICULAR PURPOSE.

The End

http://www.spinwardstars.com/frontier/fal.html

#### WPA Supplicant

Copyright (c) 2003-2012, Jouni Malinen <j@w1.fi> and contributors All Rights Reserved.

This software may be distributed, used, and modified under the terms of BSD license:

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- Neither the name(s) of the above-listed copyright holder(s) nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT OWNER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.











iperf, Copyright (c) 1999,2000,2001,2002,2003,2004,2005 The Board of Trustees of the University of Illinois All Rights Reserved.

Iperf performance test
Mark Gates
Ajay Tirumala
Jim Ferguson
Jon Dugan
Feng Qin
Kevin Gibbs
John Estabrook
National Laboratory for Applied Network Research
National Center for Supercomputing Applications
University of Illinois at Urbana-Champaign
http://www.ncsa.uiuc.edu

Permission is hereby granted, free of charge, to any person obtaining a copy of this software (lperf) and associated documentation files (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

- \* Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimers.
- \* Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimers in the documentation and/or other materials provided with the distribution.
- \* Neither the names of the University of Illinois, NCSA, nor the names of its contributors may be used to endorse or promote products derived from this Software without specific prior written permission.

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT. IN NO EVENT SHALL THE CONTIBUTORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.










EC815 GS VI.indd 22 1/17/2020 5:00:18 PM













CT0-B466-A

© CANON INC. 2019





